

# Bodine B60 Emergency Ballast



Bodine B60 Emergency Ballast. The B60 emergency ballast works in conjunction with an AC ballast to convert new or existing fluorescent fixtures into emergency lighting. The emergency ballast consists of a high-temperature nickel-cadmium battery, charger and electronic circuitry in one compact red case. For damp locations; two-lamp emergency illumination; end-of-lamp-life compatible.

For damp locations; Two-lamp emergency illumination; end-of-lamp-life compatible.

Upgrade – replaces model BDL600

UL Listed

Factory or Field Installation (Damp)

Illumination Time

90 Minutes

Initial Light Output

600 – 700 Lumens

Full Warranty

3 Years (NOT pro-rata)

Voltage

120/277 VAC, 60 Hz

AC Input Current

280 mA

AC Input Power Rating

3.5 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

280 mA

Recharge Time

24 Hour

Charging Indicator Light

LED

Temperature Rating (Ambient)

Damp Location

0°C to +50°C

(32°F to 122°F)

Dry Location

0°C to +55°C

(32°F to 131°F)

Dimensions

9.4" x 2.4" x 1.5"

(238 mm x 60 mm x 38 mm)

Mounting Center 8.9" (226 mm)

Weight

2.5 lbs. (1.13 kg)

Model B60 is warranted for three (3) full years from date of purchase. Please see detailed warranty information on the Signify official website.

For other items like the Bodine B60 Emergency Ballast [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).