

Bodine B30 Emergency Ballast



Bodine B30 Emergency Ballast. Works in conjunction with an AC ballast to convert new or existing fluorescent fixtures into emergency lighting. The emergency ballast consists of a nickel-cadmium battery, charger and electronic circuitry in one case. Can be used with most 17 – 215 W (2' – 8') T5, T8, T9, T10 or T12 fluorescent lamps without integral starters AC/DC Output for T5 or T8 lamps suitable for one- or two-lamp Operation for up to 3500 Lumen Output. Universal Input 120V through 277V.

UL Listed for the US and Canada
Factory or Field Installation
(Indoor and Damp)

Illumination Time
90 Minutes

Initial Light Output
900 – 3500 Lumens

Full Warranty
5 Years (NOT pro-rata)

Universal Input Voltage
120-277 VAC, 50/60 Hz

AC Input Current
110 mA

AC Input Power Rating

8.5 Watts

Test Switch/Charging Indicator Light

Two-Wire Illuminated Test Switch (2W-ITS)

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

280 mA

Recharge Time

24 Hours

Temperature Rating (Ambient)

0°C to +50°C

(32°F to 122°F)

Dimensions

16.6" x 2.8" x 2.85"

(422 mm x 71 mm x 73 mm)

2' (610 mm) Flexible Conduit

Mounting Center 16.05" (408mm)

Weight

7.5 lbs. (3.41 kg)

For other items like the Bodine B30 Emergency Ballast [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).