

# Bodine BSL23 LED Emergency Driver



Bodine BSL23 LED Emergency Driver. The BSL23 emergency LED driver works in conjunction with an AC LED driver that has an output current not to exceed 1.5 A, convert new or existing LED fixtures into emergency lighting. The emergency driver consists of a high-temperature nickel-cadmium battery, charger and electronic circuitry in one compact red case.

## **Benefits:**

Emergency Illumination for Lower Wattage LED fixtures

For Indoor or Damp Locations

## **Specifications**

**UL Component Recognized** For Factory Installation only (Indoor and Damp)

**Illumination Time** 90 Minutes

**Full Warranty** 5 Years (NOT pro-rata)

**Dual Input Voltage** 120/277 VAC, 60 Hz

**AC Input Current** 280 mA

**AC Input Power Rating** 2.0 W

**Output Voltage** 3.0 to 20.0 VDC

**Output Current** 410 mA (Maximum)

**Output Power** 4.5 W (Maximum)

**Test Switch/Charging Indicator Light** Illuminated Test Switch

**Battery** High-Temperature, Maintenance-Free Nickel-Cadmium  
Battery 7- to 10-Year Life Expectancy

**Battery Charging Current** 250 mA

**Recharge Time** 24 Hours

**Temperature Rating (Ambient)** 0°C to +50°C (32°F to 122°F)

**Dimensions** 9.4" x 2.4" x 1.5" (238 mm x 60 mm x 38 mm)  
Mounting Center 8.9" (226 mm)

**Weight** BSL23 – 1.8 lbs. (0.82 kg)

For other items like the Bodine BSL23 LED Emergency Driver 4.5  
Watts Output Power [click here](#).

For more information on Bodine's line of lighting solutions  
[click here](#).