

Bodine B4CF2PC Emergency Ballast



Bodine B4CF2PC Emergency Ballast includes 23" of 1/2" conduit and can be used with multiple compact fluorescent lamp configurations. Specification grade; One- or two- lamp parallel operation emergency illumination. The B4CF2P emergency ballast works in conjunction with an AC ballast to convert new or existing fluorescent fixtures into emergency lighting.

UL Listed
(UL 924 Emergency Lighting Equipment)
Factory or Field Installation (Damp)

Illumination Time
90 Minutes

Initial Light Output
Up to 925 Lumens @ 25°C

Full Warranty
5 Years (NOT pro-rata)

Dual Input Voltage
120/277 VAC, 60 Hz

AC Input Current
330 mA

AC Input Power Rating
4 Watts

Test Switch
Single Pole

Battery
High-Temperature, Maintenance-Free
Nickel-Cadmium Battery
7- to 10-Year Life Expectancy

Battery Charging Current
220 mA

Recharge Time
36 Hours

Charging Indicator Light
LED

Temperature Rating (Ambient)
0°C to +50°C (32°F to +122°F)

B4CF2PC (With Conduit)
9.9" x 2.6" x 1.5" (251 mm x 66 mm x 38 mm)
23" (584 mm) of 1/2" Diameter – Flex Conduit
Mounting Center 9.4" (239 mm)

Weight
B4CF2PC (With Conduit) 3.6 lbs. (1.6 kg)

Model B4CF2PC is warranted for five (5) full years from date of purchase. Please see detailed warranty information on the Signify official website.

For other items like the Bodine B4CF2PC Emergency Ballast [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).