

# Bodine BHD65U Hazardous Location Emergency Driver



Bodine BHD65U Hazardous Location Emergency Driver

Hazardous Locations One- or Two-Lamp Illumination

Universal Input (120 through 277). The BHD65U Universal Input emergency ballast works in conjunction with an AC ballast to convert fluorescent fixtures into emergency lighting. The emergency ballast handles a wide range of input voltages and frequencies and consists of a high temperature nickel cadmium battery, charger, hermetically sealed relays and electronic circuitry in one compact red case.

Benefits:

- For Class I, Division 11 Fixtures
- Universal input (120 through 277 VAC, 50/60 Hz)
- One or Two-lamp operation

Specifications:

UL COMPONENT RECOGNIZED

Factory Installation Only

(Damp)

Illumination Time

90 Minutes (Standard)

120 Minutes (One 32 W T8)

Initial Light Output

300 – 700 Lumens

Full Warranty

3 Years (NOT pro-rata)

Universal Input Voltage

120 Through 277 VAC, 50 or 60 Hz

AC Input Current

75 mA

AC Input Power Rating

6.0 Watts

Test Switch

Double Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

280 mA

Recharge Time

24 Hours

Charging Indicator Light

LED

Temperature Rating (Ambient)

0°C to + 50°C (32°F to 122°F)

Dimensions

9.4" x 2.6" x 1.5"

(238 mm x 67 mm x 38 mm)

Mounting Center 8.9" (226 mm)

Weight

3.4 lbs. (1.5 kg)

For other items like the Bodine BHD65U Hazardous Location  
Emergency Driver [click here](#).

For more information on Bodine's line of lighting solutions  
[click here](#).