

Bodine LP600 Fluorescent Emergency Ballast



Bodine LP600 Fluorescent Emergency Ballast. Low-Profile for Space-Limited Fixtures, standard and H0 T5 and T8 Lamps. End-of-Lamp-Life Compatible. The LP600 low-profile emergency ballast works in conjunction with a low-profile or standard-size AC ballast to convert new or existing standard or high-output T5 and T8 fluorescent fixtures into unobtrusive emergency lighting. The emergency ballast consists of a high-temperature nickelcadmium battery, charger and electronic circuitry in one compact case

Benefits

- Low Profile case
- Emergency mode lumen output up to 1325 lumens
- End-of-Lamp-Life Compatible
- Compatible with TLED lamps (see Table 1)

Specifications

UL Listed for US and Canada

Listed to UL924 and tested to CSA 22.2 No. 141

Field or Factory Installation (Indoor and Damp) Output Class 2 Compliant

Illumination Time

90 Minutes

Initial Light Output

600 – 1325 Lumens @ 25°C

Full Warranty

5 Years (NOT pro-rata)

Dual Input Voltage

120/277 VAC, 60 Hz

AC Input Current

180 mA

AC Input Power Rating

3.0 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

165 mA

Recharge Time

24 Hours

Charging Indicator Light

LED

Temperature Rating (Ambient)

0°C to +50°C (32°F to 122°F)

Dimensions

21.5" L x 1.18" W x 1.18" H

(546 mm x 30 mm x 30 mm)

Mounting Center 21.1" (536 mm)

Weight

3.3 lbs. (1.5 kg)

For other items like the Bodine LP600 Fluorescent Emergency Ballast [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).