

# Bodine BSL310M LED Emergency Driver



Bodine BSL310M LED Emergency Driver. Emergency LED driver. Listed for field installation. Class 2 output. 10 Watts output power.

## Benefits:

- Listed for field or factory installation – UL 924 and CSA C22.2 No. 141.

## Emergency Lighting Compliant.

- Smart Charger Technology for low energy consumption.
- Meets CEC Title 20 (California Energy Commission) efficiency standards.
- Class 2 output – UL 1310 Certified, CSA 22.2 No 223-M91 compliant.
- Emergency mode lumen output of up to 1300 lumens
- Universal input (120-277 VAC).
- 2 wire input helps reduce wiring errors.
- Compatible with a variety of LED strip manufacturers.
- Compatible with AC drivers and LED loads rated for Class 2.
- RoHS Compliant.

## Specifications

UL Listed for US and Canada

Listed to UL924 and tested to CSA 22.2, No. 141

For Field or Factory Installation

(Indoor and Damp)

Illumination Time

90 Minutes

Full Warranty

5 Years (NOT pro-rata)

Universal Input Voltage

120-277 VAC, 50/60 Hz

AC Input Power Rating

4.0 W (Maximum)

Output Voltage

15-50 VDC

Output Power

10.4 W (Maximum)

Test Switch/Charging Indicator Light

Illuminated Test Switch

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Recharge Time

24 Hours

Temperature Rating (Ambient)

0°C to +55°C (32°F to 131°F)

Dimensions

15.34" x 2.25" x 1.16" (369 mm x 58 mm x 30 mm)

Mounting Center 15.0" (356 mm)

Weight

3.45 lbs. (1.56kg)

For other items like the Bodine BSL310M LED Emergency Driver  
[click here.](#)

For more information on Bodine's line of lighting solutions

[click here.](#)