

Bodine ELI-S-20 Emergency Lighting Inverter



Bodine ELI-S-20 Emergency Lighting Inverter. Sinusoidal (Sine Wave) Output 20 or 25 Watts Power Auto Select 120 or 277 VAC Code-Compliant 90-Minute Runtime.

Benefits

Sine wave output

- Fused output load connections
- Works with LED and fluorescent fixtures
- Ideal for (but not limited to) screw-base LED lamps
- Auto Select feature helps reduce wiring errors
- Compatible with AC (line voltage) driven TLED lamps
- Remote-mounting up to 250 feet maximum

Specifications

UL Listed for US and Canada

Listed to UL924 and tested to CSA 22.2 No. 141

Field or Factory Installation (Indoor and Damp) Output Class 2 Compliant

Illumination Time

90 Minutes

Maximum Load Power (including AC ballast/driver)

20 W (0°C to 50°C) UL and CSA

25 W (0°C to 45°C) UL only

Full Warranty

5 years (NOT pro-rata)

AC Input Voltage

120 or 277 VAC, 60 Hz

AC Input Current

65 mA

AC Input Power Rating

8.0 W

Output Voltage

120/277 VAC (Auto Select), 60Hz

Output Current

120 V, 165 or 210 mA 277 V, 72 or 90 mA

Transfer Time

2 to 5 seconds

Test Switch

Single Pole (Momentary)

Battery

High-Temperature, Maintenance-Free ,
Nickel-Cadmium Battery,
7- to 10-year life expectancy

Battery Charging Current

250 mA

Recharge Time

24 Hours

Charging Indicator Light

LED

Temperature Rating (Ambient)

32° F to 122° F (0° C to 50° C) for 20 W

32° F to 113° F (0° C to 45° C) for 25 W

Weight

5 lbs. (2.3 kg)

For other items like the Bodine ELI-S-20 Emergency Lighting Inverter [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).