

# WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL



WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL. The LMRH-102 2-Button IR Remote Control is a handheld on/off personal control device for convenient control of any loads connected to Digital Lighting Management (DLM) room controllers. It uses an infrared transceiver to communicate with a DLM system via any DLM IR-enabled devices.

The LMRH-102 operates on battery power and transmits a digital signal for on or off whenever a pushbutton is pressed by a user. By default, the top button controls the first load in the system and the bottom button controls the second load. Button assignments may be quickly reconfigured using Push n' Learn. The LMRH-102 will work with any DLM local network, operating loads one and two, if in default mode, or the loads it has been configured to control.

## Features

Provides infrared (IR) control of two lighting loads or zones in a DLM system

- Hidden configuration button for easy access to Push n' Learn™
- Communicates with DLM local network through any DLM IR-enabled device
- Battery operated
- Includes wall mount holster and all necessary mounting

## hardware

- Each button can control individual or multiple loads
- LEDs confirm button presses
- The product meets the materials restrictions of RoHS

## Specifications

Operates on 3 AAA 1.5 volt batteries (included)

- DLM local network connection: IR transceiver
  - Range of IR transmission: up to 32 ft. (10m)
  - Angle of IR reception: 30°
- 2 control buttons, each with LED indicator
- Hidden configuration button to access
- Push n' Learn
- Weight: approx. 3.2 oz. (91g), without mounting bracket
- Operating conditions: for indoor use only; 32-95°F (0-35°C); 5-95% RH, non-condensing
- FCC part 15 compliant
- Five year warranty

For other items like the WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL [click here](#).

For more information on WattStopper's line of lighting control solutions [click here](#).