

WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL



WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL. The LMRH-102 2-Button IR Remote Control is a handheld on/off personal control device for convenient control of any loads connected to Digital Lighting Management (DLM) room controllers. It uses an infrared transceiver to communicate with a DLM system via any DLM IR-enabled devices.

The LMRH-102 operates on battery power and transmits a digital signal for on or off whenever a pushbutton is pressed by a user. By default, the top button controls the first load in the system and the bottom button controls the second load. Button assignments may be quickly reconfigured using Push n' Learn. The LMRH-102 will work with any DLM local network, operating loads one and two, if in default mode, or the loads it has been configured to control.

Features

Provides infrared (IR) control of two lighting loads or zones in a DLM system

- Hidden configuration button for easy access to Push n' Learn™
- Communicates with DLM local network through any DLM IR-enabled device
- Battery operated
- Includes wall mount holster and all necessary mounting

hardware

- Each button can control individual or multiple loads
- LEDs confirm button presses
- The product meets the materials restrictions of RoHS

Specifications

Operates on 3 AAA 1.5 volt batteries (included)

- DLM local network connection: IR transceiver
 - Range of IR transmission: up to 32 ft. (10m)
 - Angle of IR reception: 30°
- 2 control buttons, each with LED indicator
- Hidden configuration button to access
- Push n' Learn
- Weight: approx. 3.2 oz. (91g), without mounting bracket
- Operating conditions: for indoor use only; 32-95°F (0-35°C); 5-95% RH, non-condensing
- FCC part 15 compliant
- Five year warranty

For other items like the WattStopper LMRH-102 2-BUTTON IR REMOTE CONTROL [click here](#).

For more information on WattStopper's line of lighting control solutions [click here](#).